

Vassos Nicolaou
Navigate
2009
Premiere
2009



The setup and the execution of the electroacoustic part
of this work requires a Computer Music Designer (Max expert).

Table of Contents

Table of Contents	2
Work related information	3
Performance details	3
Detailed staff	3
Realisation	3
Event	3
Useful links on Brahms	3
Version related information	4
Documentalist	4
Realisation	4
No other version available	4
Electronic equipment list	5
Computer Music Equipment	5
Audio Equipment	5
Files	6
Instructions	7
Audio, Loudspeakers and MIDI setup	7
Software installation	8
System calibration and tests	9
Audio tests	9
Keyboard test	10
Midi mixer test	10
Initialization routine	11
Patch presentation	11
Score following	11
Performance notes	12
Soundfiles	12
Other performances	14
Program note	16

Work related information

Performance details

- Oct. 10, 2009, Paris, Centre Pompidou, concert Tremplin

Publisher : Inédit

Detailed staff

- 1 flute, 1 oboe, 1 clarinet, 1 bass clarinet, 1 bassoon, 1 horn, 1 trumpet [en ut] , 1 tenor/bass trombone, 2 percussionists, 1 electronic/MIDI keyboard/synthesizer, 1 piano, 1 violin, 1 second violin, 1 viola, 1 cello, 1 double bass

Realisation

- Serge Lemouton

Event

- Concert Tremplin - Sat 10 Oct 2009 - Centre Pompidou, Grande Salle - -

Useful links on Brahms

- [Navigate for ensemble and electronics \(2008-2009\), 18mn](#)
- [Vassos Nicolaou](#)

Version related information

Performance date: Oct. 10, 2009

Documentation date: Oct. 10, 2009

Version state: valid, validation date : May 3, 2018, update : May 6, 2021, 3:10 p.m.

Documentalist

You noticed a mistake in this documentation or you were really happy to use it? Send us feedback!

Realisation

- Serge Lemouton (Computer Music Designer)
- Jeremy Henrot (Sound engineer)

Version length: 17 mn

Default work length: 18 mn

No other version available

Electronic equipment list

Computer Music Equipment

- 1 MacPro - *Apple Desktops* (Apple)
OS X 10.5.8
- 1 Max/MSP - *Max* (Cycling74)
version 5.0.7
- 1 UFX - *Sound Board* (RME)
- 1 KX 88 - *MIDI Keyboard* (Yamaha)
- 1 BCF 2000 - *MIDI Mixer* (Behringer)
- 1 Footswitch / Sustain Pedal - *Footswitch / Sustain Pedal*
- 1 MIDI booster - *Booster*

Audio Equipment

- 1 Mixing Console - *Mixing Console*
with a minimum of 24 microphone inputs (only 21 needed for the orchestra), 16 aux outputs (sub mixes sent to computer), 8 line inputs (returns from computer), and additional 8 outputs for the PA. The 16 aux outs/8line ins should be digital to keep noise and added delay to a minimum.

Files

File	Type	Author(s)	Comment
keyboardist score	Score	Vassos Nicolaou	
conductor score	Score	Vassos Nicolaou	
Stage Setup	Setup	Jeremie Henrot	Stage setup and microphones
Sampler sound banks	Sound banks	serge Lemouton	Re-use of some samplor sound banks designed for the piece for vibraphone.
Multi-track recording of the first rehearsal	Simulation files	serge Lemouton	To test the patch, this multitrack Digital Performer session contains a multi-track recording of 2 complete different version of the score, along with a midi track.
Max patch and library	Patch	serge Lemouton	


Instructions

Audio, Loudspeakers and MIDI setup

IRCAM <small>Centre de Recherche Musiques</small>	
plan n°: 001	Tremplin Cursus 2
date : 10/10/2009	CGP - Grande salle
Etude: Jérémie HENROT Tel: 00 33 1 44 78 14 21 Fax: 00 33 1 44 78 15 40 henrot@ircam.fr	


Concert Tremplin Cursus 2

10 Octobre 2009 - CGP Grande Salle
Nicolaou



Patch

1	violon 1	DPA 4061
2	Violon 2	DPA 4061
3	alto	DPA 4061
4	Cello	DPA 4021
5	C.Basse	DPA 4021
6	Flute	DPA 4088
7	Cor	Re 10
8	Trompette	PL 10
9	Trombone	PL 10
10	Hautbois	AKG C535
11	Clarinette 1	AKG C535
12	Clarinette 2	AKG C535
13	Basson	AKG C535
14	Piano L	DPA 4021
15	Piano R	DPA 4021
16	Acc Percu 1	M88
17	OH Percu 1L	Shure KSM 137
18	OH Percu 1R	Shure KSM 137
19	OH Percu 2L	Shure SM 81
20	OH Percu 2R	Shure SM 81
21	Acc Percu 2	M88
22		



Software installation

Copy the following folders on the computer :


- tremplin-pat
- otemo-Machfive (because Navigate is using some sampled instruments programmed for Otemo)

Start MaxMSP 5.

Set Max file preferences to:

- tremplin-pat/lib
- tremplin-pat/Tremplin-banks
- Otemo-Machfive

Check the DSP Status setup :



Open the Tremplin-18 patch with MaxMSP 5.

Don't worry about the warning in max window about the missing `supervp.play~` or `r1_oper_init`, this objects are not used.


System calibration and tests

Audio tests

Instrument audio channel assignment :

1. Flute
2. Oboe
3. Clarinet
4. Bass Clarinet
5. Bassoon
6. Horn
7. Trumpet
8. trombone
9. Percussion 1
10. Percussion 2
11. Piano
12. Violin 1
13. Violin 2
14. Viola
15. Cello
16. Contrabass

Check that each instrument is received correctly in the patcher ensemble. (also accessible through the "inputs" shortcuts menu)



Check the 6-channel Spatialisateur audio outputs.

The seventh audio channel output is the direct sound from the software sampler, it should be sent directly to the stage monitor situated close to the keyboard player.

Keyboard test

Check the midi connection from the Midi keyboard to the computer.

You can select the midi port in the blue midikeyboard patcher.

Play notes and program changes on the keyboard.

To test the sustain pedal : press program 7 and play in the higher half of the keyboard (it is an electric piano preset). Check that the stage monitor level is correct.

If necessary, you can invert the sustain pedal polarity with the toggle found in the patcher samplers.

The lowest note of the keyboard (A0, MIDI21) is stopping all the soundfiles currently playing.

Midi mixer test

Check the Midi mixer.

You can select the midi port in the MIDIMIX patcher.

You should adjust the fader assignments in order to control the following parameters (check that the main window max sliders are reacting) :

1. spat1-level
2. spat2-level
3. spat3-level
4. crosssynthesis1-level
5. crosssynthesis2-level
6. crosssynthesis3-level

7. samplers-level

Initialization routine

To init the piece, press the init button.

Patch presentation


The screenshot displays the Tremplin-18 software interface, which is divided into several functional panels:

- soundfile:** Contains a dropdown menu for '015-018-piano-chord.wav', a '+2' button, a '98' value field, and several 'mute~' buttons. Below these are several vertical sliders for 'p splay', 'p supervp.play', 'p samplers', 'p cross', 'p harmonizers', 'p resonators', and 'p spectral'.
- Mix:** A large grid-based mixer with columns labeled 'did', 'smp', 'cross', 'Harm', 'spectral', and 'reson'. Rows are labeled 'spat1' through 'spat3', 'cross1' through 'cross3', 'harm1' through 'harm3', 'sdelai1', 'sdelay2', 'reson', and 'HP1' through 'HP6'. A 'p matrice' button and a 'clear' button are also present.
- Spats:** Three vertical sliders labeled 'Spat_Oper1', 'Spat_Oper2', and 'Spat_Oper3', with a 'p SPAT' button below them.
- ensemble:** Features a red vertical bar labeled 'Tempo' with a 'p Tempo' button. Below it are buttons for 'p midi', 'p SETTINGS', and 'p TODO'. A 'p MIDIMIX' button is also visible.
- Score following (Antescofo):** A complex panel with a 'p keys' button, a 'key: 'c'' label, and a large '1' in a box. It includes a 'mes1' label in red, a 'p midiProgram' button, and various numerical displays and control elements.
- shortcuts:** A panel with a 'matrice' dropdown, a 'p init' button, and a 'Dac on/off' button.
- sequences:** A list of sequences including 'coll otemo-soundfiles 1', 'coll otemo-midfiles 1', 'coll otemo-sequences 1', and 'p midi-sequences-menu'.
- Presets:** A panel with 'p keys' and 'p midikeyboard' buttons, a 'mes1' dropdown, and a 'store >' button.

Vassos Nicolaou : Navigate for ensemble and electronics (2009)

Score following

The only section where antescofo is used for score following correspond to the "pgm 15" in the keyboard, the antescofo score called "marimba-pgm15.asco" is loaded automatically. This is the only "score" still used in the piece.



Performance notes

The ensemble should be slightly amplified.

During the performance, mix the electronic sounds and transformations according to the orchestral level.

The electronic part should be balanced with the instrumental sounds, and can be also louder at some points, make it live !

Soundfiles

The soundfile list is located in the section1-sf coll, in the blue midikeyboard patcher.

The syntax for each line of this coll is the following :

- note-number : program followed by midi-note (for example 360 is middleC in program number 3)
- soundfile name (the score bar number is almost always indicated in the sound name)
- voice
- output-channel
- level in dB (0 corresponds to the original level)

```

133, sfplay 015-tam-tam.aif 4 4 0;
136, sfplay 015-018-piano-chord.wav 2 2 0;
178, sfplay 019-oboe-Fis5.aif 1 1 0;
236, sfplay 022-BCI-Cb-interval.wav 2 2 0;
235, sfplay 025-B1-fade-SD.aif 3 3 0;
237, sfplay 025-B1-quick-SD.aif 4 4 -52;
240, sfplay 025-Trb-C2.aif 1 1 0;
241, sfplay 026-F2-fade-SD-Tom.wav 3 3 0;
242, sfplay 027-F2-Cb-SD.aif 3 3 0;
229, sfplay 032-Cb-F1.aif 2 2 0;
246, sfplay 036-B3-SD-medium.aif 3 3 0;
281, sfplay 038-Trpt-A4-SD-quick.wav 4 4 0;
269, sfplay 038-Trpt-A4-SD-slow.wav 2 2 0;
282, sfplay 039-CI-trill-SD-slower.aif 3 3 0;
284, sfplay 039-CI-trill-SD-slow.aif 4 4 0;
243, sfplay 042-Cb-G2-SD-attack.aif 1 1 0;
256, sfplay 042-Cello-Gis3-SD-medium.aif 2 2 0;

```

283, sfplay 043-Brass-H3-SD-medium.wav 3 3 0;
271, sfplay 043-Brass-H3-SD-quick.wav 4 4 0;
263, sfplay 050-Oboe-SD-slow.aif 1 1 0;
264, sfplay 052-Cl-E4-SD-slow.aif 2 2 0;
270, sfplay 052-Trpt-Ais4-SD-very-slow.aif 3 3 0;
458, sfplay 060-Trpt-Ais4-SD-very-slow.aif 4 4 0;
479, sfplay 066-trpt-F5-slowest.aif 1 1 0;
464, sfplay clbb-tgr-E4.aif 2 2 -6;
478, sfplay 068-trpt-F5-slowestB.aif 3 3 0;
436, sfplay 073-Pno-H1-SD-figures.aif 4 4 0;
424, sfplay 073-Pno-H1-SD-slow-figures.aif 2 2 0;
477, sfplay 074-Vln1-F5-SD-figures.aif 1 1 0;
490, sfplay 077-Vln-F650-SD-figures.wav 3 3 0;
484, sfplay 077-Vln-F650-SD-figures-Del.aif 2 2 0;
489, sfplay 077-Vln-F650-SD-figuresB.aif 1 1 0;
471, sfplay 079-Trpt-H3-SD-figures.aif 4 4 0;
474, sfplay 081-sndA.aif 2 2 0;
475, sfplay 081-sndA.aif 3 3 0;
565, sfplay clbb-tgr-F4.aif 4 4 -6;
576, sfplay 091-097-Pno-chord-SD-A.wav 1 1 0;
574, sfplay 091-097-Pno-chord-SD-A.wav 3 3 0;
579, sfplay 099-Pno-chord-SD-B.wav 2 2 0;
588, sfplay 102-Cl-slapE4a.aif 3 3 0;
590, sfplay 104-Cl-slapE4a.aif 4 4 0;
580, sfplay 106-Cl-slapE4a.aif 1 1 0;
592, sfplay 107-Cl-slapE4a.aif 2 2 0;
529, sfplay 112-F2-1-2-3-all.aif 3 3 0;
581, sfplay 113-Pno-chord-SD-B.aif 4 4 0;
577, sfplay 115-Pno-chord-SD-A.aif 1 1 0;
541, sfplay 119-Vc-sync.aif 3 3 0;
536, sfplay 123-C2-1-2-3-all.aif 4 4 0;
589, sfplay 077-Vln-F650-SD-figures.wav 1 1 0;
591, sfplay 077-Vln-F650-SD-figures.wav 2 2 0;
570, sfplay 132-part-coda-A.aif 3 3 0;
573, sfplay 132-part-coda-B.aif 1 1 0;
575, sfplay 132-part-coda-C.aif 2 2 0;
582, sfplay 135-F2-4rth.aif 1 1 0;
728, sfplay 143-audio4-Sp2.aif 3 3 0;
729, sfplay 143-audio3-Sp2.aif 1 1 0;
733, sfplay 144-Vln1-Sp1.aif 2 2 0;
734, sfplay 145-elec15-Sp1.aif 3 3 0;
735, sfplay 145-audio4-Sp2.aif 4 4 0;
736, sfplay 148-BassCl-Sp1.aif 1 1 0;
737, sfplay 145-elec15B-Sp1.aif 2 2 0;
738, sfplay 146-Vln1-Sp1.aif 3 3 0;
740, sfplay 147-Oboe-Sp3.aif 4 4 0;
741, sfplay 148-BassCl-Sp1.aif 1 1 0;
742, sfplay 148-elec15-Sp1.aif 2 2 0;
743, sfplay 149-audio3-Sp2.aif 3 3 0;
744, sfplay 149-elec15-Sp1.aif 4 4 0;
746, sfplay 150-Oboe-Sp3.aif 1 1 0;
754, sfplay 151-CelloA-Sp1.aif 2 2 0;
755, sfplay 151-elec15-Sp1.aif 3 3 0;
756, sfplay 152-elec15-Sp1.aif 4 4 0;
757, sfplay 155-elec15-Sp1.aif 1 1 0;
822, sfplay 158-elec15-Sp1.aif 2 2 0;
824, sfplay 159-elec15-Sp1.aif 3 3 0;
825, sfplay 161-elec15-Sp1.aif 4 4 0;
863, sfplay 162-elec15-Sp1.aif 1 1 0;
850, sfplay 163-elec15-Sp1.aif 2 2 0;
861, sfplay 165-elec15-Sp1.aif 3 3 0;
847, sfplay 167-elec15-Sp1.aif 4 4 0;
856, sfplay 169-elec15-Sp1.aif 1 1 0;
855, sfplay 170-elec15-Sp1.aif 2 2 0;
854, sfplay 172-elec15-Sp1.aif 3 3 0;
852, sfplay 173-elec15-Sp1.aif 4 4 0;
862, sfplay 174-elec15-Sp1.aif 1 1 0;
848, sfplay 175-tune-filt-Aud1-Sp1.aif 2 2 0;

859, sfplay 175-elec15-Sp1.aif 3 3 0;
 844, sfplay 176-tune-filt-Aud1-Sp1.aif 4 4 0;
 897, sfplay 178-elec15-Sp1.aif 1 1 0;
 898, sfplay 179-tune-filt-Aud1-Sp1.aif 2 2 0;
 842, sfplay 180-tune-filt-Aud1-Sp1.aif 3 3 0;
 900, sfplay 181-elec15-Sp1.aif 4 4 0;
 901, sfplay 182-elec15-Sp1.aif 1 1 0;
 839, sfplay 182-tune-filt-Aud1-Sp1.aif 2 2 0;
 837, sfplay 183-elec15-Sp1.aif 3 3 0;
 936, sfplay 186-tune-filt-Aud1-Sp1.aif 4 4 0;
 937, sfplay 191-tune-filt-Aud1-Sp1.aif 1 1 12;
 944, sfplay 195-tune-filt-Aud1-Sp1.aif 2 2 0;
 966, sfplay 195-197-Fis2.aif 3 3 0;
 968, sfplay 195-197-gis2.aif 4 4 0;
 970, sfplay 201-Trb-Ais2.aif 1 1 0;
 1079, sfplay 244-ascending.aif 3 3 -6;
 1081, sfplay 244-descending.aif 1 1 0;
 1708, sfplay 389-breathings-orig-CS-mixed.aif 2 2 -6;

Other performances

Navigate has been performed in Miami in march 2012 by members of the New World Symphony. The conductor was Mr Michael Linville (Michael.Linville@nws.edu) and the sound engineers was Mr Roberto Toledo (Roberto.Toledo@nws.edu) and Brian Shepard.

Everything seems to run smoothly, under Max 6.
 Here is a mail Brian Shepard wrote after the performance :

From: Brian Shepard

Date: 16 mars 2012 18:26:43 HNEC

To: Vassos Nicolaou , serge lemouton

Cc: Roberto Toledo , Mike Golubitsky , Michael Linville , Justin Trieger

Subject: Re: *Navigate*

I would like to second Roberto's comments and provide some further information about what I did with the patch.

First off, I immensely enjoyed "Navigate" and the opportunity to be involved. Congratulations on such a cool piece!

As the person who did the Max modifications, these are the things I did to the Max patch (as best I can remember). Mike, if there's something I forgot out, please add it...

1. Created a MIDI Program change offset—since some keyboards begin their program change numbers with 1 and others with 0, it was confusing for our keyboard player to always have to press a button one-off from what was indicated in the score. I simply made a little fix to make the keyboard agree with the *Navigate* interface on program change number
2. Added individual meters and gain controls for all channels in the Outputs patcher
3. Added an 8th channel to the dac~ in the Outputs patcher (with meter and gain control) to serve as a separate tap for the sampler to the main Left/Right speakers. As Roberto mentioned, we were unsure of whether or not the sampler sound should only come from its monitor or be included in the L/R speakers. Since all the other instruments on stage were producing sound at their physical location AND being placed in the L/R speakers, we opted to do the same for the sampler. Since we needed separate gain controls for the keyboard monitor and the L/R speakers, I added the 8th channel and split the sampler receive signal in the Outputs patcher
4. Added MIDI fader control from the MIDI mixer (fader 8) to be a master fader control for all the gains in the Outputs patcher

Here are my suggestions for future versions of the patch:


1. Remove (or hide) all the elements that are not intrinsic to "Navigate" from the interface. When I initially began troubleshooting this piece, I frequently went down wrong paths because of all the extra objects in the interface that don't actually do anything in "Navigate." I realize this patcher is designed to be used with a number of different compositions, but all the extra stuff was quite confusing.
2. Make it abundantly clear in the instructions, the score, the keyboard part—and in the patcher itself—that all the events are triggered from the keyboard part. When I first began working on this patcher, I didn't have a copy of the keyboard part and it took me awhile to realize that was how I could get events to trigger. Once I discovered that, it all made sense. However, the part that our keyboard player had was apparently an older version that didn't have some of the needed information in it. We downloaded and printed the pdf file in the link Serge provided and that one was correct. I'm not sure where the earlier version came from, but that also added to the confusion

3. Related to #2, add a simple way to trigger events without the keyboard part. This will be extremely helpful for tech setup and testing purposes
4. As Roberto mentioned the levels between the different samples varied greatly. I didn't have time to address this while in Miami other than with a fader on the sampler and instructions to the computer operator, but I would suggest going through, and balancing the levels of all the samples so that they are at approximately the same amplitude. I would also consider adding a compressor to the output of the sampler.
5. Related to #3, the velocity response of the samples also varied greatly. On some samples, changing the key velocity, even slightly, caused a huge change in the amplitude of the sample
6. Since many MIDI keyboards these days also have sliders on them, add a MIDI fader control from the keyboard to the keyboard monitor signal. That way, the keyboard player can easily adjust their own monitor level,

Again, it was a really cool experience to work on this and I hope my comments help lead to more performances. Congratulations!

-- Brian

Dr. Brian K. Shepard
Assistant Professor of Pedagogical Technology
Thornton School of Music
University of Southern California
840 West 34th Street, MUS 308
Los Angeles, CA 90089-0851
Phone: 213.821.4152
Fax: 213.740.3217
Office Location: LPB G110
Email: brian.shepard@usc.edu
<http://www.briankshepard.com>

© IRCAM 

This documentation is licensed under a [Creative Commons Attribution-NonCommercial-NoDerivatives 4.0 International License](https://creativecommons.org/licenses/by-nc-nd/4.0/).

Program note

La pièce se découpe en trois parties. La première regorge de techniques non conventionnelles de jeu instrumental. Les sons se présentent souvent comme de brefs coups de pinceau sur une toile. La musique peut être perçue comme un accompagnement des *Scènes de l'enfer* de Hieronimus Bosch.

Dans la deuxième partie, des enveloppes (*crescendi, diminuendi*) sont appliquées aux sons et les modèlent à la manière du vent façonnant le sable au Sahara. Ces enveloppes sont contrôlées avec précision par des motifs rythmiques, eux-mêmes contrôlés par des changements de tempo. Je voulais donner l'impression au public de naviguer parmi des sons déjà existants. Par ailleurs, des sons très courts sont joués dans des agglomérats rythmiques comportant des mouvements géométriques rapides et chaotiques.

Dans la dernière partie, le tempo reste toujours rapide. J'ai introduit des figures « reconnaissables » dans mes matériaux en m'inspirant du phénomène de pareidolie* et je les ai composées de manière virtuose pour les instruments. Des enveloppes sont une fois encore appliquées, cette fois sur des structures globales et des couches multiples qui s'interpénètrent.

La partie électronique développe les nuances sonores de la partie instrumentale. Grâce à une synthèse croisée en temps réel, les sons instrumentaux interagissent digitalement avec des sons de nature complètement différente, créant des espaces artificiels. Les parties acoustique et électronique sont compatibles harmoniquement et établissent des relations hétérophoniques, comme si l'une reflétait l'autre dans un miroir.

Vassos Nicolaou, programme de la création, Ircam, le 10 octobre 2009.

Version documentation creation date: None, update date: May 6, 2021, 3:10 p.m.